

## AZZA PT-5IT (Intel i430TX) Motherboard

### CPU Dual-Voltage Table

1 = JUMPERED (closed)

0 = UNJUMPERED (open)

JP 1-2	JP 3-4	JP 5-6	JP 7-8	JP 9-10	V <sub>CC2</sub> Core (V)	Core (set voltage)	V <sub>CC3</sub> I/O (V)
1	1	1	1	1	1.94		3.45
1	1	1	1	0	2.54		3.45
1	1	1	0	1	2		3.45
1	1	1	0	0	2.81		3.45
1	1	0	1	1	1.98		3.45
1	1	0	1	0	2.72		3.45
1	1	0	0	1	2.06		3.45
1	1	0	0	0	3.14		3.45
1	0	1	1	1	1.95		3.45
1	0	1	1	0	2.6		3.45
1	0	1	0	1	2.02		3.45
1	0	1	0	0	2.89		3.45
1	0	0	1	1	2		3.45
1	0	0	1	0	2.79		3.45
1	0	0	0	1	2.08		3.45
<b>1</b>	<b>0</b>	<b>0</b>	<b>0</b>	<b>0</b>	3.22	<b>3.2 V</b>	3.45
0	1	1	1	1	1.94		3.45
<b>0</b>	<b>1</b>	<b>1</b>	<b>1</b>	<b>0</b>	2.54	<b>2.5 V</b>	3.45
0	1	1	0	1	2		3.45
0	1	1	0	0	2.81		3.45
0	1	0	1	1	1.98		3.45
<b>0</b>	<b>1</b>	<b>0</b>	<b>1</b>	<b>0</b>	2.72	<b>2.7 V</b>	3.45
0	1	0	0	1	2.06		3.45
0	1	0	0	0	3.14		3.45
<b>0</b>	<b>0</b>	<b>1</b>	<b>1</b>	<b>1</b>	1.95	<b>1.95 V</b>	3.45
<b>0</b>	<b>0</b>	<b>1</b>	<b>1</b>	<b>0</b>	2.6	<b>2.6 V</b>	3.45
0	0	1	0	1	2.02		3.45
<b>0</b>	<b>0</b>	<b>1</b>	<b>0</b>	<b>0</b>	2.89	<b>2.9 V</b>	3.45
<b>0</b>	<b>0</b>	<b>0</b>	<b>1</b>	<b>1</b>	2	<b>2.0 V</b>	3.45
<b>0</b>	<b>0</b>	<b>0</b>	<b>1</b>	<b>0</b>	2.79	<b>2.8 V</b>	3.45
<b>0</b>	<b>0</b>	<b>0</b>	<b>0</b>	<b>1</b>	2.08	<b>2.1 V</b>	3.45
0	0	0	0	0	3.19		3.45

### CPU Single-Voltage Table

1 = JUMPERED (closed)

0 = UNJUMPERED (open)

JP 1-2	JP 3-4	JP 5-6	JP 7-8	JP 9-10	Voltage
0	1	0	0	0	3.3 V
1	0	0	0	0	3.5 V

### Front-Side Bus (FSB) Table

1 = JUMPERED (closed)

0 = UNJUMPERED (open)

JP5	JP6	JP7	FSB (MHz)	PCI (MHz)
1-2	1-2	1-2	50	25
1-2	1-2	2-3	55	27.5
2-3	1-2	1-2	60	30
1-2	2-3	1-2	66	33.3
2-3	1-2	2-3	75	37.5
1-2	2-3	2-3	83	41.7

### CPU Frequency Multiplier Table

1 = JUMPERED (closed)

0 = UNJUMPERED (open)

JP8	JP9	JP10	Multiplier
0	0	0	1.5
1	0	0	2
1	1	0	2.5
0	1	0	3
0	0	0	3.5
1	0	1	4
1	1	1	4.5
0	1	1	5
0	0	1	5.5
1	0	0	6

### Notes:

AMD K6+ needs to have System BIOS set to NOT CACHEABLE in the BIOS