

Part No. 209374-A  
November 2000

4401 Great America Parkway  
Santa Clara, CA 95054

# Setting Up the BayStack Instant Internet 100-S Unit

**NORTEL**  
NETWORKS™

## Copyright © 2000 Nortel Networks

All rights reserved. November 2000.

The information in this document is subject to change without notice. The statements, configurations, technical data, and recommendations in this document are believed to be accurate and reliable, but are presented without express or implied warranty. Users must take full responsibility for their applications of any products specified in this document. The information in this document is proprietary to Nortel Networks NA Inc.

## Trademarks

NORTEL NETWORKS is a trademark of Nortel Networks.

BayStack, Instant Internet, and the Nortel Networks logo are trademarks of Nortel Networks.

All other trademarks and registered trademarks are the property of their respective owners.

## Statement of conditions

In the interest of improving internal design, operational function, and/or reliability, Nortel Networks NA Inc. reserves the right to make changes to the products described in this document without notice.

Nortel Networks NA Inc. does not assume any liability that may occur due to the use or application of the product(s) or circuit layout(s) described herein.

## USA requirements only

### Federal Communications Commission (FCC) Compliance Notice: Radio Frequency Notice

**Note:** This equipment has been tested and found to comply with the limits for a Class A digital device, pursuant to Part 15 of the FCC rules. These limits are designed to provide reasonable protection against harmful interference when the equipment is operated in a commercial environment. This equipment generates, uses, and can radiate radio frequency energy. If it is not installed and used in accordance with the instruction manual, it may cause harmful interference to radio communications. Operation of this equipment in a residential area is likely to cause harmful interference, in which case users will be required to take whatever measures may be necessary to correct the interference at their own expense.

## European requirements only

### EN 55 022 statement

This is to certify that the Nortel Networks BayStack Instant Internet 100-S is shielded against the generation of radio interference in accordance with the application of Council Directive 89/336/EEC, Article 4a. Conformity is declared by the application of EN 55 022 Class A (CISPR 22).

**Warning:** This is a Class A product. In a domestic environment, this product may cause radio interference, in which case, the user may be required to take appropriate measures.

**Achtung:** Dieses ist ein Gerät der Funkstörgrenzwertklasse A. In Wohnbereichen können bei Betrieb dieses Gerätes Rundfunkstörungen auftreten, in welchen Fällen der Benutzer für entsprechende Gegenmaßnahmen verantwortlich ist.

**Attention:** Ceci est un produit de Classe A. Dans un environnement domestique, ce produit risque de créer des interférences radioélectriques, il appartiendra alors à l'utilisateur de prendre les mesures spécifiques appropriées.

---

## EC Declaration of conformity

This product conforms to the provisions of the R&TTE Directive 1999/5/EC.

## Japan/Nippon requirements only

### Voluntary Control Council for Interference (VCCI) Statement

この装置は、情報処理装置等電波障害自主規制協議会（VCCI）の基準に基づくクラス A 情報技術装置です。この装置を家庭環境で使用すると電波妨害を引き起こすことがあります。この場合には使用者が適切な対策を講ずるよう要求されることがあります。

## Taiwan requirements

### Bureau of Standards, Metrology and Inspection (BSMI) Statement

#### 警告使用者:

這是甲類的資訊產品，在居住的環境中使用時，可能會造成射頻干擾，在這種情況下，使用者會被要求採取某些適當的對策。

## Canada requirements only

### Canadian Department of Communications Radio Interference Regulations

This digital apparatus (BayStack Instant Internet 100-S) does not exceed the Class A limits for radio-noise emissions from digital apparatus as set out in the Radio Interference Regulations of the Canadian Department of Communications.

### Règlement sur le brouillage radioélectrique du ministère des Communications

Cet appareil numérique (BayStack Instant Internet 100-S) respecte les limites de bruits radioélectriques visant les appareils numériques de classe A prescrites dans le Règlement sur le brouillage radioélectrique du ministère des Communications du Canada.

### Canada CS-03 rules and regulations

**Notice:** The Industry Canada label identifies certified equipment. This certification means that the equipment meets telecommunications network protective, operational and safety requirements as prescribed in the appropriate Terminal Equipment Technical Requirements document(s). The Department does not guarantee the equipment will operate to the user's satisfaction.

Before installing this equipment, users should ensure that it is permissible to be connected to the facilities of the local telecommunications company. The equipment must also be installed using an acceptable method of connection. The customer should be aware that compliance with the above conditions may not prevent the degradation of service in some situations.

Repairs to certified equipment should be coordinated by a representative designated by the supplier. Any repairs or alterations made by the user to this equipment, or equipment malfunctions, may give the telecommunications company cause to request the user to disconnect the equipment.

Users should ensure for their own protection that the electrical ground connections of the power utility, telephone lines and internal metallic water pipe system, if present, are connected together. This precaution may be particularly important in rural areas.

**Caution:** Users should not attempt to make such connections themselves, but should contact the appropriate electric inspection authority, or electrician, as appropriate.

**Notice:** For equipment using loopstart lines, please note that the Ringer Equivalence Number (REN) assigned to each terminal device provides an indication of the maximum number of terminals allowed to be connected to a telephone interface. The termination on an interface may consist of any combination of devices subject only to the requirement that the sum of the Ringer Equivalence Numbers of all the devices does not exceed 5. The REN is located on the "FCC Rules Part 68" label located on the bracket of the module or on the back of the unit.

## Canada CS-03 -- Règles et règlements

**Avís:** L'étiquette d'Industrie Canada identifie le matériel homologué. Cette étiquette certifie que le matériel est conforme aux normes de protection, d'exploitation et de sécurité des réseaux de télécommunications, comme le prescrivent les documents concernant les exigences techniques relatives au matériel terminal. Le Ministère n'assure toutefois pas que le matériel fonctionnera à la satisfaction de l'utilisateur.

Avant d'installer ce matériel, l'utilisateur doit s'assurer qu'il est permis de le raccorder aux installations de l'entreprise locale de télécommunication. Le matériel doit également être installé en suivant une méthode acceptée de raccordement. L'abonné ne doit pas oublier qu'il est possible que la conformité aux conditions énoncées ci-dessus n'empêche pas la dégradation du service dans certaines situations.

Les réparations de matériel homologué doivent être coordonnées par un représentant désigné par le fournisseur. L'entreprise de télécommunications peut demander à l'utilisateur de débrancher un appareil à la suite de réparations ou de modifications effectuées par l'utilisateur ou à cause de mauvais fonctionnement.

Pour sa propre protection, l'utilisateur doit s'assurer que tous les fils de mise à la terre de la source d'énergie électrique, des lignes téléphoniques et des canalisations d'eau métalliques, s'il y en a, sont raccordés ensemble. Cette précaution est particulièrement importante dans les régions rurales.

**Avertissement:** L'utilisateur ne doit pas tenter de faire ces raccordements lui-même; il doit avoir recours à un service d'inspection des installations électriques, ou à un électricien, selon le cas.

**Avís:** Veuillez prendre note que pour tout appareillage supportant des lignes de type "loopstart," l'indice d'équivalence de la sonnerie (IES) assigné à chaque dispositif terminal indique le nombre maximal de terminaux qui peuvent être raccordés à une interface. La terminaison d'une interface téléphonique peut consister en une combinaison de quelques dispositifs, à la seule condition que la somme d'indices d'équivalence de la sonnerie de tous les dispositifs n'excède pas 5. Le REN figure sur l'étiquette "FCC Rules Part 68" située sur le support du module ou à l'arrière de l'unité.

## Modular components used in this assembly

This product contains a base unit and possibly one or more of the following Communication and Network Connection Options Devices. Please refer to your specific product for a description of what option cards (if any) are included. Compliance Statements for all the following devices are on file and available on request.

---

## FCC Part 68 compliance statement

This equipment complies with Part 68 of FCC Rules. All direct connections to telephone network lines must be made using standard plugs and jacks compliant with FCC Part 68. Please note the following:

1. You are required to request service from the telephone company before you connect the unit to a network. When you request service, you must provide the telephone company with the following data:
  - When you request ISDN “U” Interface Service, you must provide the telephone company with
    - The Facility Interface Code: 02IS5
    - The Service Order Code(s) (SOC): 6.0F
    - The required Universal Service Order Code (USOC) jack: RJ49C
  - When you request ISDN “S/T” Interface Service, you must provide the telephone company with
    - The Service Order Code(s) (SOC): 6.0N
    - The make, model number, and FCC Registration number of the NT1
 

**Note:** ISDN S/T cannot be directly connected to the network.
  - When you request Primary Rate ISDN Service, you must provide the telephone company with
    - The Facility Interface Code: 04DU9-1SN (1.544 MB, ESF framing format with B8ZF coding)
    - The Service Order Code(s) (SOC): 6.0F
    - The required Universal Service Order Code (USOC) jack: RJ48C
2. Your telephone company may make changes to its facilities, equipment, operations, or procedures that could affect the proper functioning of your equipment. The telephone company will notify you in advance of such changes to give you an opportunity to maintain uninterrupted telephone service.
3. If the unit causes harm to the telephone network, the telephone company may temporarily discontinue your service. If possible, they will notify you in advance, but if advance notice is not practical, you will be notified as soon as possible and will be informed of your right to file a complaint with the FCC.
4. If you experience trouble with the unit, please contact the Nortel Networks Technical Solutions Center in your area for service or repairs. Repairs should be performed only by service personnel authorized by Nortel Networks.
 

United States	1-800-2LANWAN
Valbonne, France	33-4-92-96-69-68
Sydney, Australia	61-2-9927-8800
Tokyo, Japan	81-3-5740-1700
5. You are required to notify the telephone company when you disconnect the unit from the network.

## UL listing/C-UL listing

This information technology equipment is UL-Listed and C-UL-Listed for the uses described in this and accompanying documents.

## Connecting an Instant Internet unit to the network

Important safety information

To avoid contact with electrical current:

- Never install electrical wiring during an electrical storm
- Never install telephone jacks in wet locations unless that jack is specifically designed for wet locations
- Use caution when installing or modifying telephone lines
- Use a screwdriver and other tools with insulated handles
- You and those around you should wear safety glasses or goggles
- Do not place telephone wiring or connections in any conduit, outlet or junction box containing electrical wiring

**Warning:** Do not work on your telephone wiring if you wear a pacemaker. Telephone lines carry electrical current.

Installation of inside wire may bring you close to electrical wire, conduit, terminals and other electrical facilities. Extreme caution must be used to avoid electrical shock from such facilities. You must avoid contact with all such facilities.

- Telephone wiring must be at least 6 feet from bare power wiring or lightning rods and associated wires, and at least 6 inches from other wire (antenna wires, doorbell wires, wires from transformers to neon signs), steam or hot water pipes, and heating ducts.
- Before working with existing inside wiring, check all electrical outlets for a square telephone dial light transformer and unplug it from the electrical outlet. Failure to unplug all telephone transformers can cause electrical shock.
- Do not place a jack where it would allow a person to use the telephone while in a bathtub, shower, swimming pool, or similar hazardous location.
- Protectors and grounding wire placed by the service provider must not be connected to, removed, or modified by the customer.

## Specific information related to different types of communication connections

### Connecting an Instant Internet unit containing an analog modem

It is not necessary to notify the telephone company before installing the modem. However, the telephone company may request the telephone number(s) to which the unit is connected and the related FCC information including the FCC Part 68 registration number and the ringer equivalence number.

Be sure that the telephone line you are connecting the modem to is a standard analog line and not a digital (PBX), party, or coin telephone line. If the modem is malfunctioning, it may affect the telephone lines. In this case, disconnect the modem until the source of the difficulty is traced.

### Connecting an Instant Internet unit containing an ISDN modem with NT


When connecting this version of the product to the network, avoid contact with the Telecommunications lead wire. Telephone wiring can carry dangerous voltage from electrical faults or lightning.

The product is equipped with a standard 8-pin RJ-49C jack for connection to the ISDN network.

If you need to add wiring to your facility, refer to the National ISDN Users Forum document NIUF 433-94 ISDN Wiring and Powering Guidelines (Residence and Small Business).

## Connecting an Instant Internet unit containing an ISDN modem without NT1

This version of the product is equipped with two standard 8-pin RJ-45 jacks for connection to the NT1 (the BRI line can be attached to either jack, and the unused jack can be used to connect a second ISDN device).



At the product interface point, the interface cable must be wired “straight-through” (pin 1 at one end connected to pin 1 at the other end, pin 2 to pin 2, etc.), and must have at least the middle 4 pins (pins 2, 3, 4, and 5) connected. The cables included in your package are wired in this fashion.

Your NT1 must be properly connected to your ISDN service; check with your service provider.

If you need to add wiring to your facility, refer to the National ISDN Users Forum document NIUF 433-94 ISDN Wiring and Powering Guidelines (Residence and Small Business).

**Avis:** L'étiquette d'Industri Canada identifie le matériel homologué. Cette étiquette certifie que le matériel est conforme à certaines normes de protection, d'exploitation et de sécurité des réseaux de télécommunications. Toutefois, le Ministère n'assure pas que le matériel fonctionnera à la satisfaction de l'utilisateur.

Avant d'installer ce matériel, l'utilisateur doit assurer qu'il soit permis de le raccorder aux installations de l'entreprise locale de télécommunications. Le matériel doit également être installé en suivant une méthode de raccordement acceptée. Dans certains cas, les fils intérieurs de l'entreprise utilisés pour un service individuel à ligne unique peuvent être prolongés au moyen d'un dispositif de raccordement homologué (cordon rallonge téléphonique interne). L'abonné ne doit pas oublier qu'il est possible que la conformité aux conditions énoncées ci-dessus n'empêchent pas la dégradation du service dans certaines situations. Actuellement, les entreprises de télécommunication ne permettent pas que l'on raccorde leur matériel à des jacks d'abonné, sauf dans les cas précis prévus par les tarifs particuliers de ces entreprises.

Les réparations de matériel homologué doivent être effectuées par un centre d'entretien canadien autorisé désigné par le fournisseur. La compagnie de télécommunications peut demander à l'utilisateur de débrancher un appareil à la suite de réparations ou de modifications effectuées par l'utilisateur, ou à cause de mauvais fonctionnement.

Pour sa propre protection, l'utilisateur doit assurer que tous les fils de mise à la terre de la source d'énergie électrique, des lignes téléphoniques et des canalisations d'eau métalliques, s'il y en a, sont raccordés ensemble. Cette précaution est particulièrement importante dans les régions rurales.

**Avertissement:** L'utilisateur ne doit pas tenter de faire ces raccordements lui-même; il doit avoir recours aux services d'un électricien.

L'indice de charge (IC) assigné à chaque dispositif terminal indique, pour éviter toute surcharge, le pourcentage de la charge totale qui peut être raccordée à un circuit téléphonique bouclé utilisé par ce dispositif. La termination du circuit bouclé peut être constituée de n'importe quelle combinaison de dispositifs, pourvu que la somme des indices de charge de l'ensemble des dispositifs ne dépasse pas 100.

L'indice de charge se trouve sur le modem.

## Nortel Networks NA Inc. software license agreement

**NOTICE:** Please carefully read this license agreement before copying or using the accompanying software or installing the hardware unit with pre-enabled software (each of which is referred to as “Software” in this Agreement). BY COPYING OR USING THE SOFTWARE, YOU ACCEPT ALL OF THE TERMS AND CONDITIONS OF THIS LICENSE AGREEMENT. THE TERMS EXPRESSED IN THIS AGREEMENT ARE THE ONLY TERMS UNDER WHICH NORTEL NETWORKS WILL PERMIT YOU TO USE THE SOFTWARE. If you do not accept these terms and conditions, return the product, unused and in the original shipping container, within 30 days of purchase to obtain a credit for the full purchase price.

**1. License grant.** Nortel Networks NA Inc. (“Nortel Networks”) grants the end user of the Software (“Licensee”) a personal, nonexclusive, nontransferable license: a) to use the Software either on a single computer or, if applicable, on a single authorized device identified by host ID, for which it was originally acquired; b) to copy the Software solely for backup purposes in support of authorized use of the Software; and c) to use and copy the associated user manual solely in support of authorized use of the Software by Licensee. This license applies to the Software only and does not extend to Nortel Networks Agent software or other Nortel Networks software products. Nortel Networks Agent software or other Nortel Networks software products are licensed for use under the terms of the applicable Nortel Networks NA Inc. Software License Agreement that accompanies such software and upon payment by the end user of the applicable license fees for such software.

**2. Restrictions on use; reservation of rights.** The Software and user manuals are protected under copyright laws. Nortel Networks and/or its licensors retain all title and ownership in both the Software and user manuals, including any revisions made by Nortel Networks or its licensors. The copyright notice must be reproduced and included with any copy of any portion of the Software or user manuals. Licensee may not modify, translate, decompile, disassemble, use for any competitive analysis, reverse engineer, distribute, or create derivative works from the Software or user manuals or any copy, in whole or in part. Except as expressly provided in this Agreement, Licensee may not copy or transfer the Software or user manuals, in whole or in part. The Software and user manuals embody Nortel Networks’ and its licensors’ confidential and proprietary intellectual property. Licensee shall not sublicense, assign, or otherwise disclose to any third party the Software, or any information about the operation, design, performance, or implementation of the Software and user manuals that is confidential to Nortel Networks and its licensors; however, Licensee may grant permission to its consultants, subcontractors, and agents to use the Software at Licensee’s facility, provided they have agreed to use the Software only in accordance with the terms of this license.

**3. Limited warranty.** Nortel Networks warrants each item of Software, as delivered by Nortel Networks and properly installed and operated on Nortel Networks hardware or other equipment it is originally licensed for, to function substantially as described in its accompanying user manual during its warranty period, which begins on the date Software is first shipped to Licensee. If any item of Software fails to so function during its warranty period, as the sole remedy Nortel Networks will at its discretion provide a suitable fix, patch, or workaround for the problem that may be included in a future Software release. Nortel Networks further warrants to Licensee that the media on which the Software is provided will be free from defects in materials and workmanship under normal use for a period of 90 days from the date Software is first shipped to Licensee. Nortel Networks will replace defective media at no charge if it is returned to Nortel Networks during the warranty period along with proof of the date of shipment. This warranty does not apply if the media has been damaged as a result of accident, misuse, or abuse. The Licensee assumes all responsibility for selection of the Software to achieve Licensee’s intended results and for the installation, use, and results obtained from the Software. Nortel Networks does not warrant a) that the functions contained in the software will meet the Licensee’s requirements, b) that the Software will operate in the hardware or software combinations that the Licensee may select, c) that the operation of the Software will be uninterrupted or error free, or d) that all defects in the operation of the Software will be corrected. Nortel Networks is not obligated to remedy any Software defect that cannot be reproduced with the latest Software release. These warranties do not apply to the Software if it has been (i) altered, except by Nortel Networks or in accordance with its instructions; (ii) used in conjunction with another vendor’s product, resulting in the defect; or (iii) damaged by improper environment, abuse, misuse, accident, or negligence. **THE FOREGOING WARRANTIES AND LIMITATIONS ARE EXCLUSIVE REMEDIES AND ARE IN LIEU OF ALL OTHER WARRANTIES EXPRESS OR IMPLIED, INCLUDING WITHOUT LIMITATION ANY WARRANTY OF MERCHANTABILITY OR FITNESS FOR A PARTICULAR PURPOSE.** Licensee is responsible for the security of its own data and information and for maintaining adequate procedures apart from the Software to reconstruct lost or altered files, data, or programs.

---

**4. Limitation of liability.** IN NO EVENT WILL NORTEL NETWORKS OR ITS LICENSORS BE LIABLE FOR ANY COST OF SUBSTITUTE PROCUREMENT; SPECIAL, INDIRECT, INCIDENTAL, OR CONSEQUENTIAL DAMAGES; OR ANY DAMAGES RESULTING FROM INACCURATE OR LOST DATA OR LOSS OF USE OR PROFITS ARISING OUT OF OR IN CONNECTION WITH THE PERFORMANCE OF THE SOFTWARE, EVEN IF NORTEL NETWORKS HAS BEEN ADVISED OF THE POSSIBILITY OF SUCH DAMAGES. IN NO EVENT SHALL THE LIABILITY OF NORTEL NETWORKS RELATING TO THE SOFTWARE OR THIS AGREEMENT EXCEED THE PRICE PAID TO NORTEL NETWORKS FOR THE SOFTWARE LICENSE.

**5. Government licensees.** This provision applies to all Software and documentation acquired directly or indirectly by or on behalf of the United States Government. The Software and documentation are commercial products, licensed on the open market at market prices, and were developed entirely at private expense and without the use of any U.S. Government funds. The license to the U.S. Government is granted only with restricted rights, and use, duplication, or disclosure by the U.S. Government is subject to the restrictions set forth in subparagraph (c)(1) of the Commercial Computer Software—Restricted Rights clause of FAR 52.227-19 and the limitations set out in this license for civilian agencies, and subparagraph (c)(1)(ii) of the Rights in Technical Data and Computer Software clause of DFARS 252.227-7013, for agencies of the Department of Defense or their successors, whichever is applicable.

**6. Use of Software in the European Community.** This provision applies to all Software acquired for use within the European Community. If Licensee uses the Software within a country in the European Community, the Software Directive enacted by the Council of European Communities Directive dated 14 May, 1991, will apply to the examination of the Software to facilitate interoperability. Licensee agrees to notify Nortel Networks of any such intended examination of the Software and may procure support and assistance from Nortel Networks.

**7. Term and termination.** This license is effective until terminated; however, all of the restrictions with respect to Nortel Networks' copyright in the Software and user manuals will cease being effective at the date of expiration of the Nortel Networks copyright; those restrictions relating to use and disclosure of Nortel Networks' confidential information shall continue in effect. Licensee may terminate this license at any time. The license will automatically terminate if Licensee fails to comply with any of the terms and conditions of the license. Upon termination for any reason, Licensee will immediately destroy or return to Nortel Networks the Software, user manuals, and all copies. Nortel Networks is not liable to Licensee for damages in any form solely by reason of the termination of this license.

**8. Export and re-export.** Licensee agrees not to export, directly or indirectly, the Software or related technical data or information without first obtaining any required export licenses or other governmental approvals. Without limiting the foregoing, Licensee, on behalf of itself and its subsidiaries and affiliates, agrees that it will not, without first obtaining all export licenses and approvals required by the U.S. Government: (i) export, re-export, transfer, or divert any such Software or technical data, or any direct product thereof, to any country to which such exports or re-exports are restricted or embargoed under United States export control laws and regulations, or to any national or resident of such restricted or embargoed countries; or (ii) provide the Software or related technical data or information to any military end user or for any military end use, including the design, development, or production of any chemical, nuclear, or biological weapons.

**9. General.** If any provision of this Agreement is held to be invalid or unenforceable by a court of competent jurisdiction, the remainder of the provisions of this Agreement shall remain in full force and effect. This Agreement will be governed by the laws of the state of California.

Should you have any questions concerning this Agreement, contact Nortel Networks, 4401 Great America Parkway, P.O. Box 58185, Santa Clara, California 95054-8185.

LICENSEE ACKNOWLEDGES THAT LICENSEE HAS READ THIS AGREEMENT, UNDERSTANDS IT, AND AGREES TO BE BOUND BY ITS TERMS AND CONDITIONS. LICENSEE FURTHER AGREES THAT THIS AGREEMENT IS THE ENTIRE AND EXCLUSIVE AGREEMENT BETWEEN NORTEL NETWORKS AND LICENSEE, WHICH SUPERSEDES ALL PRIOR ORAL AND WRITTEN AGREEMENTS AND COMMUNICATIONS BETWEEN THE PARTIES PERTAINING TO THE SUBJECT MATTER OF THIS AGREEMENT. NO DIFFERENT OR ADDITIONAL TERMS WILL BE ENFORCEABLE AGAINST NORTEL NETWORKS UNLESS NORTEL NETWORKS GIVES ITS EXPRESS WRITTEN CONSENT, INCLUDING AN EXPRESS WAIVER OF THE TERMS OF THIS AGREEMENT.



---

# Contents

---

<b>Preface</b> .....	<b>19</b>
Before you begin .....	19
Acronyms .....	20
Related publications .....	21
How to get help .....	23
<b>Chapter 1</b>	
<b>Introduction</b> .....	<b>25</b>
Instant Internet package .....	25
Available options .....	26
Requirements and compatibility .....	26
<b>Chapter 2</b>	
<b>Installation preparation</b> .....	<b>27</b>
Preparing for Internet access .....	27
Making decisions .....	28
Selecting an Internet service provider .....	28
Installation checklist .....	29
Installation worksheet .....	31
<b>Chapter 3</b>	
<b>Instant Internet 100-S hardware installation</b> .....	<b>33</b>
Getting to know your Instant Internet 100-S unit .....	33
Interfaces .....	36
Power cords .....	38
Setting the voltage selector switch .....	40
Instant Internet quick installation .....	41
Mounting your Instant Internet unit on the wall .....	43

<b>Chapter 4</b>	
<b>Seven-port autosensing switch specifications</b> . . . . .	<b>47</b>
Instant Internet 10/100 Ethernet switch overview . . . . .	47
Switch features . . . . .	48
RJ-45 10BASE-T/100BASE-TX Ethernet ports . . . . .	48
MDI/MDI-X autosensing capability . . . . .	49
LEDs . . . . .	49
<b>Chapter 5</b>	
<b>DIP switch settings</b> . . . . .	<b>51</b>
DIP switches . . . . .	51
Switch settings for normal operation . . . . .	52
Switch settings for special configurations . . . . .	52
Resetting your Instant Internet unit . . . . .	54
<b>Chapter 6</b>	
<b>LEDs: support and diagnostic functions</b> . . . . .	<b>57</b>
Interpreting Instant Internet LEDs . . . . .	57
LEDs 1 through 8 and Power LED at power-up sequence . . . . .	58
LEDs 1 through 8 and the Power LED during operation . . . . .	59
Using the seven-port autosensing switch LEDs for troubleshooting . . . . .	60
<b>Chapter 7</b>	
<b>Out-of-band management support</b> . . . . .	<b>61</b>
Configuring the Instant Internet unit through a PC direct connection . . . . .	62
Connecting a PC to the Instant Internet unit . . . . .	62
Configuring a direct connection . . . . .	63
Configuring the Instant Internet unit through a dial-up connection . . . . .	65
Connecting a modem to a PC . . . . .	66
Configuring modem connection settings . . . . .	66
Connecting a modem to the Instant Internet unit . . . . .	69
Connecting to an Instant Internet unit . . . . .	69

---

<b>Appendix A</b>	
<b>Technical specifications</b> .....	<b>71</b>
Physical specifications .....	71
Electrical specifications .....	71
Environmental specifications .....	72
<b>Appendix B</b>	
<b>Adapter cable pinout diagrams</b> .....	<b>73</b>
Remote access adapter cables .....	73
Null modem adapter (PC-to-PC) cable .....	73
Modem adapter cable .....	74
<b>Index</b> .....	<b>75</b>



---

## Figures

---

Figure 1	Front panel of the Instant Internet 100-S unit	34
Figure 2	Rear panel of the Instant Internet 100-S unit	35
Figure 3	Removing screws from cover of Instant Internet 100-S unit	44
Figure 4	Mounting the Instant Internet 100-S unit to the wall	45
Figure 5	DIP switches on the rear panel of the unit	51
Figure 6	Instant Internet 100-S unit LEDs	58
Figure 7	HyperTerminal Connection Description dialog box	63
Figure 8	HyperTerminal Connect To dialog box	64
Figure 9	HyperTerminal Com1 Properties dialog box	64
Figure 10	Command prompt	65
Figure 11	HyperTerminal Connection Description dialog box	67
Figure 12	HyperTerminal Connect To dialog box	67
Figure 13	HyperTerminal COM1 Properties dialog box	68
Figure 14	Null modem adapter cable pinout diagram	74
Figure 15	Modem adapter cable pinout diagram	74



---

# Tables

---

Table 1	Installation checklist .....	29
Table 2	Ethernet interfaces .....	36
Table 3	Communications interface cards .....	37
Table 4	International power cord specifications .....	38
Table 5	Voltage selector switch settings .....	40
Table 6	Switch settings for normal operation .....	52
Table 7	Switch settings for resetting the password .....	52
Table 8	Switch settings for resetting the password and user-defined configurations .....	53
Table 9	Switch settings to disable switch settings for resetting the password and user-defined configurations .....	53
Table 10	Switch settings for resetting factory default conditions .....	54
Table 11	LED status and appearance during operation .....	59
Table 12	Seven-port switch port status LEDs .....	60



---

## Preface

---

This manual describes the BayStack™ Instant Internet 100-S unit. This manual also describes what you do to install the Instant Internet™ hardware and to access the Internet.

### Before you begin

Before using this manual, you need to do two things. First, write down the model number and serial number of your Instant Internet unit. You will need this information if you have to call Nortel Networks Technical Support. Model and serial numbers are located on the back panel of your Instant Internet unit.

**Model #** \_\_\_\_\_

Example: CQ2001E52

**Serial #** \_\_\_\_\_

Example: I500E07BF224BB

Second, complete the steps outlined in [Chapter 2, “Installation preparation,” on page 27](#). The steps include:

- 1 Preparing for Internet access
- 2 Selecting an Internet service provider
- 3 Selecting the type of connection to use

## Acronyms

The following acronyms are used in this manual:

AC	Alternating Current
AUI	Attachment Unit Interface
CB	Certification Body
CEE	Certification of Electrical Equipment
CENELEC	European Committee for Electrotechnical Standardization
CHAP	Challenge Handshake Authentication Protocol
CSA	Canadian Standards Associates
cUL	Underwriter Laboratories testing to Canadian standards
dBA	Decibels Audible
DIP	Dual Inline Pins
DMZ	Demilitarized Zone
DNS	Domain Name Service
DSL	Digital Subscriber Lines
FDX	Full Duplex
HAR	Harmonized
HD	Harmonized Document
HDX	Half Duplex
IEC	International Electrotechnical Commission
IP	Internet Protocol
IPX	Internetwork Packet Exchange
ISDN	Integrated Services Digital Network
ISP	Internet Service Provider
Kb/s	Kilobits Per Second
LAN	Local Area Network
LED	Light-Emitting Diode
MB	Megabyte
Mb/s	Megabits Per Second
MDI	Medium Dependent Interface
MDI-X	Medium Dependent Interface - Crossover

MP	Multilink Protocol
NAT	Network Address Translation
NEMA	National Electrical Manufacturers Association
NOM	Norma Oficial Mexicana
NIC	Network Interface Card
NT1	Network Termination Type 1
PAP	Password Authentication Protocol
POP	Point of Presence
POTS	Plain Old Telephone Service
PPP	Point-to-Point Protocol
PPPoE	Point-to-Point Protocol over Ethernet
ROM	Read-Only Memory
SMTP	Simple Mail Transfer Protocol
SPID	Service Profile Identifier
STP	Shielded Twisted-Pair
UL	Underwriter Laboratories
UTP	Unshielded Twisted Pair
VAC	Voltage Alternating Current
WAN	Wide Area Network

## Related publications

For more information about using Instant Internet, refer to the following publications:

- *Important Information for the BayStack Instant Internet Version 7.11*  
(Part number 307603-E)  
Provides instructions for viewing documentation and installing the Instant Internet software and third-party applications (Adobe Acrobat Reader, Netscape Communicator, and AniTa Terminal Emulator).
- *Installing the BayStack Instant Internet Management Software Version 7.11*  
(Part number 209226-B)  
Provides instructions for installing the Instant Internet software.

- *Using the BayStack Instant Internet Management Software Version 7.11* (Part number 300868-G)

Provides an introduction to Instant Internet, instructions for administering the product, and procedures for using Instant Internet features.

- *Reference for the BayStack Instant Internet Remote Access Commands Version 7.11* (Part number 302005-F)

Provides instructions and commands for remotely accessing Instant Internet.

- *BayStack Instant Internet Software and Documentation Version 7.11 CD* (Part number 206664-D)

Provides manuals for using and installing the Instant Internet software and third-party applications. The CD contains the following documents:

- *Installing the BayStack Instant Internet Management Software Version 7.11*
- *Setting Up the BayStack Instant Internet 100 Unit*
- *Setting Up the BayStack Instant Internet 100-S Unit*
- *Setting Up the BayStack Instant Internet 400 Unit*
- *Setting Up the BayStack Instant Internet 400-S Unit*
- *Using the BayStack Instant Internet Management Software Version 7.11*
- *Reference for the BayStack Instant Internet Remote Access Commands Version 7.11*

You can print selected technical manuals and release notes free, directly from the Internet. Go to the [www25.nortelnetworks.com/library/tpubs/](http://www25.nortelnetworks.com/library/tpubs/) URL. Find the product for which you need documentation. Then locate the specific category (for example, “Routers” for BayStack Instant Internet products) and model or version for your hardware or software product. Use Adobe Acrobat Reader to open the manuals and release notes, search for the sections you need, and print them on most standard printers. Go to Adobe Systems Web at [www.adobe.com](http://www.adobe.com) URL to download a free copy of Acrobat Reader.

You can purchase selected documentation sets, CDs, and technical publications though the Internet at the [www1.fatbrain.com/documentation/nortel](http://www1.fatbrain.com/documentation/nortel) URL.

## How to get help

If you purchased a service contract for your Nortel Networks product from a distributor or authorized reseller, contact the technical support staff for that distributor or reseller for assistance.

If you purchased a Nortel Networks service program, contact one of the following Nortel Networks Technical Solutions Centers:

Technical Solutions Center	Telephone
EMEA	(33) (4) 92-966-968
North America	(800) 2LANWAN or (800) 252-6926
Asia Pacific	(61) (2) 9927-8800
China	(800) 810-5000

An Express Routing Code (ERC) is available for many Nortel Networks products and services. When you use an ERC, your call is routed to a technical support person who specializes in supporting that product or service. To locate an ERC for your product or service, go to the [www12.nortelnetworks.com/](http://www12.nortelnetworks.com/) URL and click ERC at the bottom of the page.



---

# Chapter 1

## Introduction

---

This chapter introduces your Instant Internet 100-S unit and describes package contents, available options for your Instant Internet unit, and any requirements and compatibility issues.



---

**Caution:** Before you install your unit, make sure that the power voltage selector switch setting matches your power voltage. For details, refer to [“Setting the voltage selector switch” on page 40.](#)

---

## Instant Internet package

The Instant Internet package contains:

- Instant Internet 100-S unit
- Depending on the type of connection you ordered, your Instant Internet package contains one or more of the following connector cables:
  - RJ-11 cable (phone cord) for a dial-up connection or 1-Meg modem connection
  - ISDN cable for an Integrated Service Digital Network (ISDN) connection
  - RJ-45 cable for a 10BASE-T or 100BASE-T Ethernet connection
  - RJ-45 crossover cable for a 10BASE-T or 100BASE-T Ethernet connection
- *Important Information for the BayStack Instant Internet* (Part number 307603-E)
- *Installing the BayStack Instant Internet Management Software Version 7.11* (Part number 209226-B)

- *BayStack Instant Internet Software and Documentation Version 7.11 CD* (Part number 206664-D)

For contents, see [“Related publications” on page 21](#).

## Available options

The Instant Internet 100-S unit is shipped with a seven-port autosensing, autonegotiating 10/100 Ethernet switch on the front of the unit, a full-duplex/half-duplex autonegotiating 10/100 megabits per second (Mb/s) Ethernet connection, and one of the following:

- A third Ethernet connection
- Internal single- or dual-analog modem
- Internal ISDN 128K card (with or without NT1) with a POTS connection
- Internal 1-Meg modem



**Note:** If your unit does not have an internal analog modem or ISDN card, disregard all references to dial-up account and dial-up configuration throughout this manual.

---

## Requirements and compatibility

Instant Internet supports the following Internet connections:

- Dial-up Point-to-Point Protocol (PPP) connection with optional Multilink Protocol (MP) at up to two times V.90
- ISDN connection using synchronous PPP and optional Multilink Protocol (MP) at up to 128 kilobits per second (Kb/s)
- Point-to-Point Protocol over Ethernet (PPPoE) connection using the 1-Meg modem or an external Ethernet device to connect to an access concentrator



**Note:** The speed of dial-up connections can vary internationally. Consult your local distributor for specifications.

---

---

## Chapter 2

# Installation preparation

---

This chapter describes steps you should follow in preparing for Internet access, explains some decisions you need to make before you install your Instant Internet 100-S unit, and provides an installation checklist and worksheet.

## Preparing for Internet access

To prepare for access to the Internet:

- 1 Obtain installation and service from your local telephone company (telco).
- 2 Obtain an Internet connection from an Internet service provider (ISP).
- 3 Connect the Instant Internet unit to your local area network (LAN).
- 4 Obtain the power cord from the Instant Internet packaging.



**Note:** Do not apply power to the Instant Internet unit until you have completed the installation steps in the procedure [“Instant Internet quick installation”](#) on page 41.

---

See [“Instant Internet quick installation”](#) on page 41 for more information.

## Making decisions

Before you can access the Internet with your Instant Internet unit, you must make the following decisions:

- Who will be your ISP?
- What type of connection will you use—dial-up connection (analog or ISDN), PPPoE connection, router connection, cable modem connection, or xDSL modem connection?

### Selecting an Internet service provider

There are thousands of ISPs from which to choose. Nortel Networks maintains an updated list of the major, national ISPs and as many local ISPs as possible. You can choose an ISP from this list, or you can locate a different one. Either way, try to choose an ISP that has a local access number so that you do not have to pay long distance charges. You can look in the yellow page directory for local or regional ISPs, or you can call a national ISP and ask if it offers local dial-up access in your area.



**Note:** Only a dial-up connection (analog or ISDN) requires this type of service from an ISP. If you are using a cable modem, xDSL modem, or external Ethernet device, you do not have to obtain dial-up service.

---

If your ISP is not on the selection list you see during Instant Internet installation, select the ! `Default` provider from the list. If you cannot connect to the Internet with the ! `Default` provider selected, do *one* of the following:

- Call Nortel Networks Technical Solutions Center. See [page 23](#) for instructions on how to contact the center.
- Send an e-mail message to [support@nortelnetworks.com](mailto:support@nortelnetworks.com).

Be sure to have your provider's name, location, and contact-person's phone number so that Nortel Networks can create a dial-up script specific to your ISP's access requirements and add your ISP to the list.

## Installation checklist

Use the checklist in [Table 1](#) to ensure a smooth installation. As you check off each item, record the information in the “[Installation worksheet](#)” on [page 31](#).

**Table 1** Installation checklist

✓	Item	Description
	Type of Account	<p>Instant Internet can provide access to your entire network through a single Internet Protocol (IP) address for unlimited access to the Internet:</p> <ul style="list-style-type: none"> <li>• If you want to use public IP addresses, request a network account.</li> <li>• If you want to use Network Address Translation (NAT) or you are using the Instant Internet unit as an IPX-to-IP gateway, request a single-user account.</li> </ul> <p>Your ISP will provide you with a user name, password, primary access phone number, optional alternate access phone number, and name server IP address. Record this information on <a href="#">page 31</a>.</p>
	Dial-up Protocols	<p>If you are using a dial-up connection in North America, ensure that your ISP supplies true IP service using PPP protocols for analog and ISDN connections. ISDN requires the synchronous PPP protocol with authentication via Password Authentication Protocol (PAP) or Challenge Handshake Authentication Protocol (CHAP).</p> <p>For a 128K connection, Multilink PPP must be supported. Some ISPs use their own proprietary protocols or, for ISDN, V.120 rate adaption. Instant Internet does not support these proprietary protocols.</p>
	ISDN Service	<p>When you obtain ISDN service, your telephone company may assign one or two Service Profile Identifier (SPID) numbers to your line. Record the SPID number(s) on <a href="#">page 31</a>.</p>
	Connect-Time Charges	<p>Some ISPs and local telephone companies charge a flat fee for unlimited connect time, and some charge fees according to the actual amount of time your Instant Internet unit is dialed in and connected. Be sure that you understand your ISP's and local telephone company's policies.</p>
	PPPoE	<p>If you are connecting using PPPoE, you must obtain a user name and password from your ISP. Record this information on <a href="#">page 31</a>.</p>

**Table 1** Installation checklist (continued)

✓	Item	Description
	Installation Information	<p>If you choose an ISP from the Nortel Networks list, you need to give only the ISP's telephone number and your user name and password for access.</p> <p>If you are using an analog or ISDN connection in North America, you can choose ! Default as your provider when you configure the unit and then enter your name servers.</p> <p>If your ISP is not on the Nortel Networks list, call the Nortel Networks Technical Solutions Center at 800-2LANWAN, Express Routing Code 169#, and provide some additional information so that Nortel Networks can create a dial-up script specific to your ISP's access requirements.</p>
	Application Information	<p>Your ISP usually offers some additional services, which you might consider:</p> <ul style="list-style-type: none"> <li>• Access to a NEWS server</li> <li>• Access to a Post Office Protocol (POP) mail server (and an SMTP relay)</li> <li>• Individual POP mail user accounts for each user</li> </ul> <p><b>NOTE:</b> Be aware that a single-user account from an ISP generally comes with only one POP e-mail account. You can arrange for additional e-mail accounts with your ISP.</p>

After completing this checklist, you are ready to begin installing the Instant Internet hardware.

---

## Installation worksheet

**ISP User Name:** \_\_\_\_\_

*This is the user name you enter to log on to your ISP account.*

**ISP Password:** \_\_\_\_\_

*This is the password you enter to log on to your ISP account.*

**ISP Connection Phone Number:** \_\_\_\_\_

*This number is the primary phone number you dial to access your ISP account.*

**ISP Connection Alternate Phone Number:** \_\_\_\_\_

*This number is an alternate or backup phone number you dial to access your ISP account if the primary phone number is not working. This phone number is optional. Not every ISP supplies an alternate phone number.*

**ISP Name Server:** \_\_\_\_\_

**ISP Name Server (optional):** \_\_\_\_\_

*The name server (or domain name server (DNS)) is the numeric IP address of your ISP's name server(s). It follows the format nnn.nnn.nnn.nnn where n is a number between 0 and 255.*

### Telephone Company Information

**ISDN SPID Number:** \_\_\_\_\_

**ISDN SPID Number:** \_\_\_\_\_

*SPID numbers are provided by your telephone company when you install an ISDN line. Usually, two SPID numbers are provided, but sometimes one and sometimes even none is provided. Only those using an ISDN connection in North America need to provide this information.*

**ISDN Phone Number required for answer (optional):** \_\_\_\_\_

**ISDN Phone Number required for answer (optional):** \_\_\_\_\_



---

## Chapter 3

# Instant Internet 100-S hardware installation

---

This chapter helps you get to know your Instant Internet unit, and provides instructions for connecting your unit to your LAN and WAN according to the type of connection you are using and for mounting your unit on a wall.

Before you install the Instant Internet hardware, make sure that you are familiar with the physical and environmental specifications of the Instant Internet 100-S unit. For more information, refer to [Appendix A, “Technical specifications,”](#) on page 71.



**Caution:** Be sure that your power voltage selector switch setting matches your power voltage. For more information, see [“Setting the voltage selector switch”](#) on page 40.

---

## Getting to know your Instant Internet 100-S unit


The front panel of your Instant Internet 100-S unit has the following indicators and connections:

- Nine LEDs (labeled 1–8 and Power) indicate various active or error conditions for your Instant Internet unit. For details, refer to [Chapter 6, “LEDs: support and diagnostic functions,”](#) on page 57.
- A seven-port autosensing, autonegotiating Ethernet switch provides a means for connecting to your network and enables you to eliminate an extra switch or hub on your LAN. Each port adapts to the correct network speed (10 Mb/s or 100 Mb/s), the duplex mode of the connected device, and the correct MDI status of the cable. For details, refer to [Chapter 4, “Seven-port autosensing switch specifications,”](#) on page 47.

- Seven 10/100 Link/Activity LEDs (labeled S1–S7) display port status for the switch. For details, refer to [Chapter 6, “LEDs: support and diagnostic functions,”](#) on page 57.
- Seven FDX LEDs (labeled S1–S7) display port mode status for the switch. For details, refer to [Chapter 6, “LEDs: support and diagnostic functions,”](#) on page 57.

[Figure 1](#) illustrates the front panel of the unit.

**Figure 1** Front panel of the Instant Internet 100-S unit




9861EA

The rear panel of the unit contains the following switches and connectors:

- A communications interface (one or two phone jacks, an ISDN jack, or a third Ethernet connection) for connecting to your telephone service company (telco) or external Ethernet connection
- Second Ethernet connection (Eth2) to connect to a router or bridge to support a Demilitarized Zone (DMZ), or to add another network segment
- AUX port to directly connect a PC or modem for out-of-band management (see [Chapter 7, “Out-of-band management support,”](#) on page 61)
- DIP switches (see [Chapter 5, “DIP switch settings,”](#) on page 51)
- Power voltage selector switch (115 or 230)
- Power supply connector and power switch

Figure 2 illustrates the rear panel of the unit.

**Figure 2** Rear panel of the Instant Internet 100-S unit



**Note:** If you have a triple-Ethernet unit, the third Ethernet connection replaces the phone jack or ISDN jack at the top of the unit.



**Warning:** The Instant Internet unit contains a lithium battery. There is a danger of explosion if the battery is replaced incorrectly. The battery should be replaced only by factory authorized personnel.

## Interfaces

Each unit has an autosensing, autonegotiating seven-port 10/100 Ethernet switch, a full-duplex/half-duplex autonegotiating Ethernet LAN interface, and one of several communications interface cards.



**Note:** The interface card(s) in your Instant Internet unit may not look exactly like those depicted in the illustrations.

[Table 2](#) describes the Ethernet interfaces available for your Instant Internet 100-S unit.

**Table 2** Ethernet interfaces






Interface name	Interface card	Type
Eth1	 <p style="text-align: right;">9865EB</p>	Seven-port Ethernet switch on the front of the unit. More information is available in <a href="#">Chapter 4, “Seven-port autosensing switch specifications,”</a> on page 47.
Eth2	 <p style="text-align: center;">Ethernet 10/100      Aux      Configuration</p> <p style="text-align: right;">9935EB</p>	Standard Ethernet interface on the back of the unit. Use Eth2 as your DMZ connection.
Eth3	 <p style="text-align: right;">9855EB</p>	Optional Ethernet interface card. Use Eth3 as your WAN connection.

Table 3 describes the communications interface cards available for your Instant Internet 100-S unit.

**Table 3** Communications interface cards





Interface name	Interface card	Type
Analog	 <p style="text-align: right;">9858EA</p>	Analog modem interface card with one RJ-11 connector for the phone (outgoing to modem) and one RJ-11 connector for the telco (incoming from wall jack).
Dual Analog	 <p style="text-align: right;">9857EA</p>	Analog modem interface card with two RJ-11 connectors for phones (outgoing to modem) and two RJ-11 connectors for telcos (incoming from wall jack).
ISDN U	 <p style="text-align: right;">9856EA</p>	ISDN U interface card (integrated NT1) with one POTS connector and one RJ-45 connector.
ISDN S/T	 <p style="text-align: right;">10047EA</p>	ISDN interface card (no integrated NT1) with one POTS connector and one RJ-45 connector.
1-Meg Modem	 <p style="text-align: right;">9874EB</p>	1-Meg modem interface card with one RJ-11 connector for the phone (outgoing to modem) and one RJ-11 connector for the telco (incoming from wall jack).

## Power cords

The AC power receptacle accepts the AC power cord (supplied). For installation outside of North America, make sure that you have the proper power cord for your region. Any cord used must have a CEE-22 standard V female connector on one end and must meet the IEC 320-030 specifications.

Table 4 lists specifications for international power cords.

**Table 4** International power cord specifications

Country/Plug description	Specifications	Typical plug
Australia: <ul style="list-style-type: none"> <li>AS3112-1981 Male plug</li> </ul>	240 VAC 50 Hz Single phase	 230FA
Continental Europe: <ul style="list-style-type: none"> <li>CEE7 standard VII male plug</li> <li>Harmonized cord (HAR marking on the outside of the cord jacket to comply with the CENELEC Harmonized Document HD-21)</li> </ul>	220 or 230 VAC 50 Hz Single phase	 228FA
US/Canada/Japan: <ul style="list-style-type: none"> <li>NEMA5-15P male plug</li> <li>UL recognized (UL stamped on cord jacket)</li> <li>CSA certified (CSA label secured to the cord)</li> </ul>	100 or 120 VAC 50–60 Hz Single phase	 227FA
United Kingdom: <ul style="list-style-type: none"> <li>BS1363 male plug with fuse</li> <li>Harmonized cord (HAR marking on the outside of the cord jacket to comply with the CENELEC Harmonized Document HD-21)</li> </ul>	240 VAC 50 Hz Single phase	 229FA

**Caution: Please read immediately.**

Inspect this power cord and determine if it provides the proper plug and is appropriately certified for use with your electrical system. Immediately discard this cord if it is inappropriate for your country's electrical system and obtain the proper cord as required by your national electrical codes or ordinances.

Refer to this product's technical documentation for detailed installation procedures to be followed by qualified service personnel.

**Achtung: Bitte sofort lesen.**

Sehen Sie nach, ob dieses Netzkabel über den richtigen Stecker verfügt und für die Verwendung in Ihrem Stromversorgungsnetz zertifiziert ist. Falls dieses Kabel nicht für das Stromversorgungsnetz in Ihrem Land geeignet ist, darf es nicht verwendet werden. Besorgen Sie sich ein Kabel, das die Vorschriften der Zulassungsbehörden in Ihrem Land erfüllt.

Die technische Dokumentation dieses Produkts enthält ausführliche Installationsanweisungen, die nur von qualifiziertem Kundendienstpersonal ausgeführt werden dürfen.

**Attention: Lisez ceci immédiatement.**

Examinez ce cordon d'alimentation pour déterminer s'il dispose de la fiche appropriée et s'il est bien agréé pour utilisation sur votre installation électrique. Débarrassez-vous en immédiatement s'il ne convient pas à l'utilisation sur le secteur électrique en usage dans votre pays et procurez-vous un cordon conforme à la réglementation nationale en vigueur.

Reportez-vous à la documentation technique de ce produit pour obtenir des instructions détaillées d'installation, destinées à un technicien qualifié.

**Attenzione: Leggere attentamente.**

Controllare questo cavo di alimentazione, verificarne il collegamento con la presa appropriata nonché la certificazione per l'uso nell'impianto elettrico posseduto. Non utilizzare assolutamente in caso tale cavo non sia adatto al sistema elettrico del paese in cui viene utilizzato e richiederne un altro certificato dall'ente nazionale di fornitura elettrica.

Per le procedure di installazione che devono essere seguite dal personale di servizio, consultare questa documentazione tecnica del prodotto.



**Precaución: Sírvase leer inmediatamente.**

Inspeccione este cable de alimentación eléctrica y determine si viene con el enchufe apropiado y está debidamente certificado para el uso con su sistema eléctrico. Si no cumple con los reglamentos del sistema eléctrico de su país, despójese de este cable de alimentación inmediatamente y obtenga el cable requerido, según las ordenanzas y códigos eléctricos nacionales.

Refiérase a la documentación técnica de este producto para recibir información detallada sobre los procedimientos que el personal calificado de reparaciones deberá seguir.



**注意：最初にお読み下さい。**

ト電源コードが、ご使用になる電力規格に適したプラグ部で、且つ適正な規格証明がついているかどうかをお確かめ下さい。

ト本電源コードがご使用の電力規格に不適格な場合はただちに使用を中止し、ご使用の国家規格・法令に定められた適切な電源コードをご使用下さい。

ト製品の取付方法につきましては、取扱技術説明書をご覧のうえ資格認定を受けたサービス・スタッフの指示に従って下さい。

## Setting the voltage selector switch

The voltage of the Instant Internet unit must match the voltage of the power source. If the switch is set to 110 and the voltage that the unit is connecting to is 200 or above, you must return the unit for repair. If the switch is set to 230 and the voltage that the unit is connecting to is 127 or below, the unit may not function properly.

Table 5 shows the voltage selector switch settings for the different voltage ranges.

**Table 5** Voltage selector switch settings

Setting	Voltage range
115	For voltages between 100 and 127
230	For voltages between 200 and 240

---

## Instant Internet quick installation

These steps guide you through the general process of installing your Instant Internet hardware.

Install your Instant Internet 100-S unit in a ventilated area that is dust free and away from heat vents, warm air exhaust from other equipment, and direct sunlight. Avoid proximity to large electric motors or other electromagnetic equipment. Be sure to choose a location near your router and LAN or WAN hubs and close to an electrical outlet.



**Note:** Before you begin the installation, make sure that the power voltage selector switch matches your power voltage (see [“Setting the voltage selector switch” on page 40](#)) and the DIP switch settings are set to normal operation (see [“Switch settings for normal operation” on page 52](#)).

---

The communications connection is necessary to provide the link between your Instant Internet unit and your Internet service provider (ISP). To ensure a proper communications connection, make sure that you have ordered the appropriate following services:

- Installation from your telco
- Service from your telco
- Internet access service from your ISP

Be sure to review the information in [“Installation checklist” on page 29](#).

If you experience problems during installation, unplug all connections, except the LAN connection, and then restart the Instant Internet unit.



**Note:** *Do not* apply power to the Instant Internet unit until you have completed the installation steps.

---

You can mount your Instant Internet unit on a wall or place it on a flat surface. If you choose not to mount the Instant Internet unit on the wall, be sure to install the unit's rubber feet. If the feet are not installed, stick the adhesive side of the feet on the spaces provided on the bottom of the unit. You need to use either the mounting brackets or the feet.

To install your Instant Internet hardware:

- 1 Do one of the following:
  - If you want to mount your Instant Internet unit on a wall, you must do so before you connect it to your LAN. Follow the procedure [“Mounting your Instant Internet unit on the wall” on page 43](#) and then return to this procedure and continue with step 2.
  - If you do not want to mount your Instant Internet unit on a wall, place the unit on any appropriately level surface that can safely support the weight of the unit and attached cables. Make sure that there is adequate space around the unit for ventilation and access to cable connectors. Allow at least 2 inches (5.1cm) on each side for proper ventilation and 5 inches (12.7cm) at the back for power cord clearance and ventilation. Continue with step 2.
- 2 With the tip of a pen, slide the power voltage selector switch to the power voltage setting that matches your power voltage. For more information, see [“Setting the voltage selector switch” on page 40](#),
- 3 Attach one end of the communications cable (analog modem, ISDN, 1-Meg modem, or Ethernet connection to a router or bridge) to the appropriate connector on the rear panel of the Instant Internet unit.

If you are using an external Ethernet device, use the Ethernet connector in the option slot (Eth3) to connect to the external device.

If you are connecting an Ethernet cable, be sure to use the proper cable (straight-through or crossover) for this connection.



**Note:** A second Ethernet connector (Eth2) is available for connecting a Demilitarized Zone (DMZ) or for connecting two LANs together. For more information on DMZs see *Using the BayStack Instant Internet Management Software Version 7.11*.

---

- 4 Attach the other end of the communications cable to the appropriate source (phone jack, ISDN jack, cable modem, 1-Meg modem, or external device).
- 5 Do one of the following:
  - To use the Instant Internet unit as your LAN switch, attach up to seven workstations to the seven-port switch on the front panel of the unit.
  - To connect the Instant Internet unit to your LAN, attach one end of the LAN cable (straight-through or crossover) to one of the ports on the seven-port switch and attach the other end of the cable to your LAN.
- 6 Plug the power cord into the rear panel of the Instant Internet unit.
- 7 Plug the power cord into an AC wall outlet.
- 8 Turn on the Instant Internet unit.

When you turn on your Instant Internet 100-S unit, the LEDs on the left side of the front panel illuminate. LED 2 glows amber when the unit is ready for configuration. For information about configuring your unit, see *Installing the BayStack Instant Internet Management Software Version 7.11*.

## Mounting your Instant Internet unit on the wall

To mount your Instant Internet unit on a wall, you will need a Phillips screwdriver (not included) and the brackets, screws, and washers provided in the wall mounting kit.



**Caution:** The screws and wall composition must be able to withstand the weight of the device, plus the additional weight of the attached network cables and power cords.



**Achtung:** Schrauben und Wand müssen so beschaffen sein, daß sie dem Gewicht des Geräts, zuzüglich des Gewichts der angeschlossenen Netzwerk- und Netzstromkabel, standhalten können.



**Attention:** Les vis de fixation et le mur doivent être capables de supporter le poids du dispositif, ainsi que des câbles réseau et cordons qui y sont rattachés.



**Attenzione:** Le viti e la struttura a muro devono essere in grado di sostenere il peso del dispositivo, oltre a quello dei cavi di rete e di alimentazione collegati.



**Precaución:** Los tornillos y la composición de la pared deben ser capaces de sostener el peso del dispositivo más el peso adicional de los cables de red y cables de alimentación conectados.




**注意:** ネジや壁の材質がデバイスとこれに接続されているネットワーク・ケーブルおよび電源コードを合わせた重さに耐える必要があります。

---

To mount your Instant Internet 100-S on the wall:

- 1 Remove the three screws from the cover on each side of your Instant Internet unit as shown in [Figure 3](#).

**Figure 3** Removing screws from cover of Instant Internet 100-S unit



- 2 Attach the front mounting brackets to your unit using the screws that you just removed from the unit.




**Note:** The mounting bracket is designed so that it will work on either side of the Instant Internet unit. Only three of the six holes in the mounting bracket are used on each side of the unit.

- 3 Position your unit on the wall vertically as shown in [Figure 4](#).

The front panel of your unit should be facing the ceiling. The bottom of your unit should be against the wall.

**Figure 4** Mounting the Instant Internet 100-S unit to the wall



9864FB

- 4 Attach your unit to the wall using the mounting screws and washers provided.



---

## Chapter 4

# Seven-port autosensing switch specifications

---

The chapter lists the key features of the seven-port autosensing switch and explains the components of the switch in detail.

### Instant Internet 10/100 Ethernet switch overview

The seven-port switch on the front of the Instant Internet unit has seven 10/100 autosensing ports. Each port automatically senses and adapts to the operating environment, regardless of the type of cable (straight-through or crossover) plugged into the port, or whether the device at the other end of the cable is an Ethernet card, such as in a PC, or another hub or switch.

The seven-port switch is designed to provide flexibility in configuring your network connections. You can use the switch to:

- Add hardware to your LAN.
- Network several computers together.
- Connect your Instant Internet unit without purchasing additional hardware.
- Replace your existing 10BASE-T or 100BASE-T hub to save space.

## Switch features

The Instant Internet 100-S unit seven-port switch offers:

- Seven RJ-45 10BASE-T/100BASE-T autosensing Ethernet ports with autonegotiation capability. The eighth port is used internally to connect to the internal Ethernet controller.
- Comprehensive 10/100 Link/Activity LEDs indicating link and activity status.
- Full-duplex (FDX) and half-duplex (HDX) mode support with one indicator LED per port.
- MDI (uplink, or crossover)/MDI-X (normal, or straight-through) autosensing capability.
- Store-and-forward switching architecture.
- One MB buffer memory.

When you plug an Ethernet cable into a port, the switch:

- Autosenses the transmission speed (10 Mb/s or 100 Mb/s) of the connected device.
- Autonegotiates with the connected device to operate in full- or half-duplex mode. If the connected device is operating in half-duplex mode only, or does not have the capability to participate in the autonegotiation process, the port defaults to half-duplex mode.
- Autosenses whether the cable is MDI or MDI-X.

### RJ-45 10BASE-T/100BASE-TX Ethernet ports

The RJ-45 10BASE-T/100BASE-TX Ethernet ports connect the switch to network devices using standard unshielded twisted pair (UTP) cable. The Instant Internet 100-S switch does not support shielded twisted-pair (STP) cable. Each port adapts to the correct network speed of 10 Mb/s or 100 Mb/s through autonegotiation with the network interface card (NIC), hub, or other switch connected to the Instant Internet unit.

## MDI/MDI-X autosensing capability

When you plug an Ethernet cable into a port, the switch autosenses whether the cable is MDI-X (normal, or straight-through) or MDI (uplink, or crossover). This feature enables you to connect the Instant Internet unit to another Ethernet connection regardless of whether you are using a straight-through cable or a crossover cable.



**Note:** Observe standard networking guidelines when you use the seven-port switch to install or connect an Instant Internet 100-S unit to additional devices.

---

## LEDs

The LEDs on the Instant Internet 100-S unit switch provide information about the performance and status of the switch including link activity, data transmission speed, and duplex mode.

For more information on LEDs, refer to [Chapter 6, “LEDs: support and diagnostic functions,”](#) on page 57.



---

## Chapter 5

# DIP switch settings


---

This chapter describes the Dual Inline Pins (DIP) switch settings for your Instant Internet 100-S unit, including those for normal operation and for resetting your unit's password and configuration settings.

## DIP switches

DIP switches enable you to configure your Instant Internet unit for a particular type of operation. There are eight DIP switches on the rear panel of your unit (Figure 5). The switches are labeled left to right from 1 to 8.

**Figure 5** DIP switches on the rear panel of the unit



9871EA

The switches have two possible positions: on and off. For the Instant Internet 100-S unit, the on position is down and the off position is up. Use a small instrument with a fine point, such as the tip of a pen or a straightened paper clip, to move the switches to the proper position. Labels on the unit indicate whether a switch is on or off, and the specific switch pattern indicates a specific configuration item.

## Switch settings for normal operation

Leave all switches *off* for normal operation, as shown in [Table 6](#).

**Table 6** Switch settings for normal operation

	1	2	3	4	5	6	7	8
OFF	•	•	•	•	•	•	•	•
ON								

## Switch settings for special configurations

During the power-up sequence, your Instant Internet 100-S unit checks the settings of the switches. You can use the switches on your unit to:

- Erase the password ([Table 7](#)), which is useful if you forget the password.
- Erase the password and other user-defined system configuration ([Table 8](#)).
- Disable the switch settings for resetting the password and user-defined configurations ([Table 9](#)).
- Reset the original default factory settings ([Table 10](#)).

[Table 7](#) shows the switch settings for resetting your unit's password.

**Table 7** Switch settings for resetting the password

	1	2	3	4	5	6	7	8
OFF				•		•		•
ON	•	•	•		•		•	

[Table 8](#) shows the switch settings for resetting your unit's password as well as some user-defined configurations.

**Table 8** Switch settings for resetting the password and user-defined configurations

	1	2	3	4	5	6	7	8
OFF				•			•	•
ON	•	•	•		•	•		



**Caution:** If you use these switch settings to reset your unit, the following user-defined settings are removed or reset: password, hosts, port mappings, and unit configuration.

[Table 9](#) shows the switch settings to disable the switch settings for resetting the password and user-defined configurations.

**Table 9** Switch settings to disable switch settings for resetting the password and user-defined configurations

	1	2	3	4	5	6	7	8
OFF			•					•
ON	•	•		•	•	•	•	

[Table 10](#) shows the switch settings for resetting your unit to factory default conditions.

**Table 10** Switch settings for resetting factory default conditions

	1	2	3	4	5	6	7	8
OFF				•				•
ON	•	•	•		•	•	•	



**Caution:** If you use these switch settings to reset your unit to the factory default conditions, the following user-defined settings are removed or reset: password, hosts, port mappings, unit configuration, access restrictions, unit registration, and encryption authorization.

**Caution:** If you purchased and installed the *3DES Encryption Module* (part number CQ1010005), you need to reinstall it.

If you used the switch settings in [Table 9](#) to disable the reset password and configuration switch settings, these settings are re-enabled.

## Resetting your Instant Internet unit

Before you reset your Instant Internet unit, be sure to back up the configuration. If you back up the configuration, you can easily restore it. For details, refer to *Using the BayStack Instant Internet Management Software Version 7.11*.

To reset your Instant Internet unit:

- 1 Turn off your unit.
- 2 Set the switches to the configuration you want.

Refer to “[Switch settings for special configurations](#)” on page 52.

- 3 Turn on your unit.

The LEDs on the front of your unit flash and then glow steadily amber, including the Power LED, when they completely match the sequence for the selected switch settings.



**Note:** If you used the switch settings in [Table 9](#) to disable the reset password and configuration switch settings, the Power LED glows amber and LEDs 1–8 flash red in the sequence of the selected switch settings.

---

- 4 Turn off your unit.
- 5 Reset the switches for normal operation.

Normal operation is when all the switches are in the off position. Refer to [“Switch settings for normal operation”](#) on page 52.

- 6 Turn on your unit.



---

## Chapter 6

# LEDs: support and diagnostic functions


---

This chapter describes how the LEDs on your Instant Internet 100-S unit work and how you can use them to interpret activity on your unit.

### Interpreting Instant Internet LEDs

The front panel of the Instant Internet 100-S unit has two sets of LEDs, the eight LEDs on the left indicate failures and operational status of the unit. The Power LED is always lit when your unit is turned on. The 14 LEDs at the bottom, center of the unit, display status and settings for the seven-port switch.

[Figure 6](#) illustrates the LEDs on the front of the Instant Internet 100-S unit.

**Figure 6** Instant Internet 100-S unit LEDs

## LEDs 1 through 8 and Power LED at power-up sequence

If a failure occurs during the power-up sequence, the Power LED glows amber, and one or more of LEDs 1 through 8 glow red. This sequence indicates a hardware problem. Call the Nortel Networks Technical Solutions Center ([page 23](#)) for assistance.

If all LEDs glow amber, or none of the LEDs illuminates, check that the power voltage selector switch setting matches your power voltage. For more information, see [“Setting the voltage selector switch” on page 40](#).



**Caution:** During normal operation, the Power LED glows green, except when updating the internal flash ROM. While updating the flash memory, the Power LED glows amber. This amber LED indicates that it is not safe to turn off the unit without potentially damaging the contents of flash memory.

## LEDs 1 through 8 and the Power LED during operation

After the power-up sequence is complete, the LEDs indicate status and activity during operation as shown in [Table 11](#).

**Table 11** LED status and appearance during operation

LED #	Color	Appearance	Meaning
Power	Green	Solid	Unit has electrical power and is turned on.
Power	Green and Amber	Solid Green and Flashing Amber	Unit is updating flash ROM. DO NOT TURN THE UNIT OFF until light returns to green.
1	Green	Blinking	Unit is operating normally.
2	Green	Solid	Unit is ready to service clients.
2	Green and Amber	Solid Green and Flashing Amber	Unit is communicating with clients.
2	Amber	Solid	Unit is ready to run setup but cannot service clients (normally occurs before unit has been configured).
3-8	Green	Solid	Indicated interface (see Note below) is online.
3-8	Green	Flashing	Indicated interface (see Note below) is dialing or attempting connection.
3-8	Green and Amber	Solid Green and Flashing Amber	Traffic is on the indicated interface.
3-8	Red	Solid	Indicated interface (see Note below) has failed.



**Note:** The “indicated interface” is the interface associated with the LED’s number. This information is available in the main dialog box of the Setup program. For more information, refer to *Using the BayStack Instant Internet Management Software Version 7.11*.

## Using the seven-port autosensing switch LEDs for troubleshooting

The seven-port autosensing switch has two LEDs for each port on the switch. The top row of these LEDs displays speed, link, and activity. The bottom row of LEDs displays whether the unit is operating in full- or half-duplex mode.

Use the LED display to help you identify the type of problem with the seven-port autosensing switch and then verify that:

- The switch is powered on.
- Each cable and port connection has the correct pin assignment and that no connectors are loose.
- The Link/Activity LED glows for each port used.

If the Link LED is not on:

- Verify that the device connected to your switch has a properly functioning power supply.
- Try using a different port on your switch to connect the device.
- Try using a different port on the device connected to your switch.

[Table 12](#) describes the LEDs that monitor the seven-port switch.

**Table 12** Seven-port switch port status LEDs

Type	Label	Color	Activity	Meaning
Port Status	10/100 Link/Activity	Green	Solid	Port is connected at 100 Mb/s
Port Status	10/100 Link/Activity	Amber	Solid	Port is connected at 10 Mb/s.
Port Status	10/100 Link/Activity	Green	Blinking	100 Mb/s activity is occurring on the port
Port Status	10/100 Link/Activity	Amber	Blinking	10 Mb/s activity is occurring on the port
Port Mode	FDX	Green	Solid	Port is operating in full-duplex mode
Port Mode	FDX	off	off	Port is operating in half-duplex mode

---

## Chapter 7

# Out-of-band management support

---

This chapter describes how to set up your Instant Internet unit for out-of-band management. This feature enables you to configure the Instant Internet unit without installing the unit on a network or loading the Instant Internet management software.

After you connect a dumb terminal or a smart terminal (for example, a PC, a Macintosh, or a UNIX workstation) and terminal emulation software (for example, HyperTerminal or ProComm Plus) to the unit's AUX port, you can use remote access commands to configure the unit. For details, refer to *Reference for the BayStack Instant Internet Remote Access Commands Version 7.11*.

You can use out-of-band management any time, including for initial configuration, troubleshooting, or daily management of the unit. This chapter describes how to use a 32-bit Windows® operating system and the HyperTerminal terminal emulation software to:

- Connect to the unit with a PC for out-of-band management. For details, refer to [“Configuring the Instant Internet unit through a PC direct connection,”](#) next. You must supply a null modem cable (also referred to as a pc-to-pc file transfer cable) to connect your PC to the Instant Internet unit.
- Configure an external modem to be used for out-of-band management. For details, refer to [“Configuring the Instant Internet unit through a dial-up connection”](#) on page 65. You must supply a modem cable to connect your dial-up modem to the Instant Internet unit.

These procedures assume that you have turned on the unit and no LEDs are glowing red. For more information on installing the Instant Internet hardware refer to [Chapter 3, “Instant Internet 100-S hardware installation,”](#) on page 33. For more information on the required connection cables, refer to [Appendix B, “Adapter cable pinout diagrams,”](#) on page 73.

## Configuring the Instant Internet unit through a PC direct connection

To configure the unit with a PC using the out-of-band management feature, you must:

- Connect the unit to the PC.
- Use terminal emulation software to configure and establish a connection.

### Connecting a PC to the Instant Internet unit

This procedure assumes that the Instant Internet unit is installed, turned on, and ready for operation. LED 2 glows amber when the unit is ready for initial configuration.



**Note:** You can connect any type of smart terminal in a similar manner.

---

To connect a PC to the Instant Internet unit:

- 1 Plug one end of the null modem cable into the AUX port on the rear of the unit.
- 2 Plug the other end of the cable into the serial port on the PC.

You can now use terminal emulation software to configure the Instant Internet unit using remote access commands.

## Configuring a direct connection

Regardless of the terminal emulation environment you use, you must set the connection speed to 115200, set the flow control to hardware (RTS/CTS), and connect the Instant Internet unit's AUX port to the PC's COM1 port.

This procedure provides instructions for configuring the HyperTerminal terminal emulation software.




**Caution:** If you are configuring the unit, wait for LED 2 to glow amber before you proceed.

To create a HyperTerminal PC connection profile:

- 1 Start the HyperTerminal software.

The Connection Description dialog box opens (Figure 7).

**Figure 7** HyperTerminal Connection Description dialog box



- 2 In the Name box, enter a name for the connection.
- 3 In the Icon area, select an icon for the connection.
- 4 Click OK.


The Connect To dialog box opens (Figure 8).

**Figure 8** HyperTerminal Connect To dialog box



- 5 From the Connect using list, select COM1, and then click OK.  
The COM1 Properties dialog box opens (Figure 9).

**Figure 9** HyperTerminal Com1 Properties dialog box



- 6 From the Bits per second list, select 115200 to set the modem speed, and then click OK.

HyperTerminal establishes a connection to the Instant Internet unit. If the Instant Internet unit is password protected, the session begins by requesting a password. Enter the password for the Instant Internet unit and then press Enter.



**Note:** If you enter an incorrect password, the message “Incorrect Login” is displayed and you are prompted to enter a correct password. You are given two more chances before Instant Internet ends the session and disconnects you.

---

When you successfully log on, the command prompt is displayed (Figure 10) and you can begin using remote access commands to configure the unit.

**Figure 10** Command prompt

```
BayStack Instant Internet(tm) version 7.11
Copyright (c) 1995-2000 Nortel Networks Corporation
ii>
```

## Configuring the Instant Internet unit through a dial-up connection

To configure the unit through a dial-up connection using the out-of-band management feature, you must:

- Connect the modem to a PC.
- Use a terminal emulation software application to configure the modem connection settings.
- Connect the modem to your Instant Internet unit.

## Connecting a modem to a PC

For this procedure, you do not need to load the modem drivers on the PC.



**Note:** You can also connect a dumb terminal in a similar manner.

---

To connect a modem to a PC:

- 1 Connect the modem's power cord to the modem and the power outlet, as described in the modem's installation instructions.
- 2 Plug one end of the DB9 serial cable into the modem.
- 3 Plug the other end of the cable into the serial (COM1) port on the PC.
- 4 Turn on the modem.


## Configuring modem connection settings

Regardless of the terminal emulation environment you use, you must set the connection speed to 115200, set the flow control to hardware (RTS/CTS), and set the modem to answer on the first ring (auto-answer) with the command string: `ats0=1&w\r`. Some modems enable you to configure the modem to auto-answer using DIP switch settings. Refer to your modem's documentation for instructions.

This procedure provides instructions for configuring modem connection settings using the HyperTerminal terminal emulation software.

To configure modem connection settings using HyperTerminal:

- 1 Start the HyperTerminal software.  
The Connection Description dialog box opens ([Figure 11](#)).

**Figure 11** HyperTerminal Connection Description dialog box

- 2 In the Name box, enter a name for the connection.
- 3 In the Icon area, select an icon for the connection.
- 4 Click OK.


The Connect To dialog box opens (Figure 12).

**Figure 12** HyperTerminal Connect To dialog box

- 5 From the Connect using list, select COM1, and then click OK.

The COM1 Properties dialog box opens (Figure 13).

**Figure 13** HyperTerminal COM1 Properties dialog box



- 6 From the Bits per second list, select 115200 to set the modem speed, and then click OK.

HyperTerminal establishes a connection to the modem and the cursor is positioned in the main HyperTerminal dialog box.

- 7 Enter:

```
ats0=1&w\r
```

This command instructs the modem to answer on the first ring and saves the settings to the modem. Some modems respond with “OK” or a similar message when the settings are saved to the modem.

- 8 Disconnect the modem from the PC.

---

## Connecting a modem to the Instant Internet unit

Before you connect the modem to the Instant Internet unit, you must turn off the unit.



**Note:** Before you continue with this procedure, be sure that you have properly configured the modem connection settings. For details, refer [“Configuring modem connection settings” on page 66](#).

---

To connect a dial-up modem to the Instant Internet unit:

- 1 Turn off the Instant Internet unit.
- 2 Plug one end of the DB9 serial cable into the AUX port on the rear of the Instant Internet unit.
- 3 Plug the other end of the cable into the modem.
- 4 Plug one end of the telephone cord into the modem and the other end into the wall phone jack.
- 5 Turn on the modem.
- 6 Turn on the Instant Internet unit.

If you are configuring the unit, wait for LED 2 to glow amber.

## Connecting to an Instant Internet unit

You can use any terminal emulation software application to dial in to the Instant Internet unit.

To connect to the Instant Internet unit:

- Dial the telephone number of the modem attached to the unit.

After you establish a connection, you can begin using remote access commands to configure the unit. For details, refer to *Reference for the BayStack Instant Internet Remote Access Commands Version 7.11*.



---

## Appendix A

# Technical specifications

---

This appendix describes the physical and environmental specifications for your Instant Internet 100-S unit.

### Physical specifications

The Instant Internet 100-S unit is 12 inches wide by 14.39 inches deep by 2.64 inches high and weighs 8.8 pounds.

### Electrical specifications

- Input voltage: 100-127Vac or 200-240Vac
- Input current: 4A or 2A
- Frequency: 50/60 Hz
- Power consumption: 85 watts maximum
- Safety agency approvals: UL listed, cUL, CB certificate and report, NOM

## Environmental specifications

The operating and nonoperating environment for the Instant Internet 100-S unit is as follows:

- Operating temperature: 0° to 40° C maximum
- Nonoperating temperature: -25° to 70° C maximum
- Operating humidity:
  - 8% minimum to 80% maximum
  - Relative humidity: noncondensing
- Nonoperating humidity
  - 5% minimum to 80% maximum
  - Relative humidity: noncondensing
- Operating altitude: 8,000 feet (2,438 meters) maximum
- Nonoperating altitude: 30,000 feet (9,144 meters) maximum
- Acoustic Noise: 53dBA at 3 feet

---

## Appendix B

# Adapter cable pinout diagrams

---

This appendix describes the pinout settings for the modem and null modem adapter cables.

### Remote access adapter cables


If you want to connect a PC or dial-up modem directly to your Instant Internet 100-S unit to configure the unit using remote access commands (out-of-band management), you must provide the connection cable. These are standard cables. You can have a cable made according to the pinout diagrams in this appendix or you can purchase the cable from any computer supply store.

For information on configuring your unit remotely, refer to *Reference for the BayStack Instant Internet Remote Access Commands Version 7.11*.

### Null modem adapter (PC-to-PC) cable

[Figure 14](#) shows the pinout settings for a null modem adapter cable (also referred to as a pc-to-pc file transfer cable). This serial cable must have two DB-9 female connectors.

Use a null modem cable to connect a PC to the Instant Internet unit's AUX port for out-of-band management.


**Figure 14** Null modem adapter cable pinout diagram

9959EA

## Modem adapter cable

Figure 15 shows the pinout settings for a modem adapter cable. This serial cable must have a DB-9 female connector and a DB-25 male connector.

Use a modem cable to connect a dial-up modem to the Instant Internet unit's AUX port for out-of-band management.

**Figure 15** Modem adapter cable pinout diagram

9958EA

---

# Index

---

## Symbols

! Default provider 28

## Numbers

1-Meg modem 26

3DES Encryption Module 54

## A

access concentrator, connection 26

acronyms 20

altitude 72

autonegotiating 26, 33, 36, 48

autosensing 26, 33, 36, 47, 48, 49, 60

AUX port 34, 61, 69

## C

cable

100BASE-T Ethernet connection 25

10BASE-T Ethernet connection 25

1-Meg modem connection 25

crossover 49

dial-up connection 25

installing 41

ISDN connection 25

MDI 49

MDI-X 49

modem 61, 74

null modem 61, 73

pc-to-pc file transfer 61, 73

pinout diagrams 73

straight-through 49

uplink 49

CHAP 29

configuration

out-of-band management 61

terminal emulation software 61

connection

dial-up 26

ISDN 26

PPPoE 26

customer support 23

## D

Demilitarized Zone (DMZ) 34, 42

DIP switch settings 52

DIP switches 51

DMZ connection 36

dumb terminal 61

## E

Ethernet connection, cable 25

external router, connection 26

## F

factory default conditions, resetting 54

full-duplex (FDX) 48, 60

## H

half-duplex (HDX) 48

HyperTerminal 61

connection profile, modem 66

connection profile, PC 63

## I

installation

checklist 29

overview 41

unit specifications 72

worksheet 31

Internet service provider

! Default provider 28

access phone number 29

additional services 30

name server 29

password 29

selecting 28

user name 29

Internet Service Provider Hotline 28

ISDN connection

configuration option 26

Multilink Protocol 26

NT1 26

provider options 30

service connection 29

SPID number 29

synchronous PPP 26

## L

LEDs

about 33

activity 59

after power-up sequence 59

full-duplex (FDX) 48, 60

half-duplex (HDX) 48

interpreting 57

Link/Activity 48, 60

normal operation 59

power-up sequence 58

red 58

seven-port autosensing switch 33, 60

status 59

troubleshooting 60

## M

MDI 49

MDI-X 49

modem

1-Meg 26

analog 26

modem cable 61, 74

Multilink Protocol (MP) 26

## N

NT1 37

null modem cable 61, 73

## O

out-of-band management 34, 61, 73

## P

package contents 25

PAP 29

password

incorrect 65

providing 65

password, resetting 52

pc-to-pc file transfer cable 61, 73

phone cord 25

physical specifications 71

power cord warnings (multilingual) 39

power switch 34

power voltage selector switch 25, 33, 34, 41, 42

PPP 26, 29

PPPoE 29

ProComm Plus 61

product support 23

protocol

analog 29

dial-up 29

ISDN 29

PPP 29

PPPoE 29

proprietary 29

publications

hard copy 22

related 21

## R

RJ-11 connector 25, 37

RJ-45 connector 25, 37

## S

seven-port autosensing switch

features 48

function 47

LAN connection 43

LEDs 57, 60

troubleshooting 60

seven-port switch

LEDs 60

smart terminal 61

specifications 72

SPID number 29

support, Nortel Networks 23

switch

power voltage selector 25, 33, 34, 41, 42

seven-port 26, 33, 36, 43, 47, 57, 60

switch settings

disabling 53

resetting the password 52

resetting to factory default conditions 54

resetting user-defined configurations 53

## T

technical publications 22

technical support 23

telco 41

temperature 72

terminal emulation software 61

COM1 port 63

connection speed 63, 66

HyperTerminal 61

modem command string 66

ProComm Plus 61

troubleshooting 60

## U

unit

acoustic noise 72

AUX port 61, 69

connecting directly, modem 69

connecting directly, PC 62, 66

electrical frequency 71

electrical specifications 71

input current 71

input voltage 71

power consumption 71

resetting 54

safety agency approvals 71

wall mounting 43

user-defined configuration, resetting 53

## W

wall mounting 43





