

Socket 370 CPU Support List										
Chipset Family	Model	PCB Version	Intel Family						Cyrix Family	
			Celeron (FC/PPGA 66MHz FSB)	Celeron (FCPGA 100MHz FSB)	Celeron (FCPGA2 100MHz FSB)	Pentium III (FCPGA-100MHz FSB)	Pentium III (FCPGA-133MHz FSB)	Pentium III (FCPGA2-133MHz FSB)	Cyrix Mill (100MHz FSB)	Cyrix Mill (133MHz FSB)
Intel 815 / 815E	CS35-SC	A	300A-700	800	Not Supported	500E-850E	533EB-1G	Not Supported	Not Supported	
	CS35-EC/EL	A	300A-700	800	Not Supported	500E-850E	533EB-1G	Not Supported	500-600	533-600
	CS65-SC/SU	A	300A-700	800	Not Supported	500E-850E	533EB-1G	Not Supported	Not Supported	
	CS65-EC	A, A2	300A-700	800-1.1G	Not Supported	500E-850E	533EB-1G	Not Supported	Not Supported	
	CS15	A1	300A-700	800	Not Supported	500E-850E	533EB-1G	Not Supported	Future VIA Cyrix III Processor	
	Intel 815E B-step	CS35-TC/TL	A	566-700	800-1.1G	≥1.2G	500E-850E	533EB-1G	1.13G-1.26G	Future VIA Cyrix III Processor
	Intel 815EP	CS60-EC	A	300A-700	800	Not Supported	500E-850E	533EB-1G	Not Supported	Not Supported
CS61-EC/EN		A	300A-700	800	Not Supported	500E-850E	533EB-1G	Not Supported	Not Supported	
CS62-TC		A	566-700	800-1.1G	Not Supported	500E-850E	533EB-1G	Not Supported		
CS62-TC		BA0	566-700	800-1.1G	≥1.2G	500E-850E	533EB-1G	1.13G-1.26G	Not Supported	
Intel 815EP B-step	CS32-TC/TL	A	566-700	800-1.1G	≥1.2G	500E-850E	533EB-1G	1.13G-1.26G	Future VIA Cyrix III Processor	
Intel 810 DC100/E	CW35-D/L/S	A, B2	300A-533	Not supported	Not Supported	Not Supported		Not Supported	Not Supported	
	CW35-D/L/S	C, C1, C2	300A-700	800-1.1G	Not Supported	500E-850E	Not Supported	Not Supported		
	CW35-E	C, C1	300A-700	800	Not Supported	500E-850E	533EB-933EB	Not Supported	Not Supported	
	CW65-D/L/S	A1	300A-533	Not supported	Not Supported	Not Supported		Not Supported		
	CW65-D/L/S	B1, C	300A-700	800	Not Supported	500E-850E	Not Supported	Not Supported		
	CW65-E	B1, C	300A-700	800	Not Supported	500E-850E	533EB-933EB	Not Supported		
Intel 810 Flex ATX	CW27	A	300A-700	800	Not Supported	500E-850E	Not Supported	Not Supported	500-600	Not Supported
	CW27-EA/EN	A	300A-700	800	Not Supported	500E-850E	533EB-1G	Not Supported	500-600	533-600
Intel 810E2	CW35-AC	A	300A-766	800	Not Supported	500E-850E	533EB-1G	Not Supported	500-600	533-600
	CW35-TC	A	566-700	800-1.1G	≥1.2G	500E-850E	533EB-1G	1.13G-1.26G	Future VIA Cyrix III Processor	
Intel 810+CH2	CW35-AS	A	300A-766	800	Not Supported	500E-850E	Not Supported	Not Supported	Future VIA Cyrix III Processor	
Intel 440BX	CB60-BX	A	300A-533	Not supported	Not Supported	Not Supported		Not Supported	Not Supported	
	CB50-BX	A	300A-533							
	CB61	A, B1	300A-700	800	Not Supported	500E-850E	Not Supported	Not Supported	500-600	Not Supported
VIA PM133	CM35-EC/SC	A	300A-700	800	Not Supported	500E-850E	533EB-1G	Not Supported	500-600	533-600
VIA Apollo (693)	CB50-V3	A	300A-533	Not supported	Not Supported	Not Supported		Not Supported	Not Supported	
	CB60-V3	A	300A-533							
VIA Apollo Pro (693A)	CA33	A	300A-766	800	Not Supported	500E-850E	533EB-933EB	Not Supported	Not Supported	
		A1	300A-766	800	Not Supported	500E-850E	533EB-933EB	Not Supported	500-600	533-600
	CA61	A, B1	300A-700	800	Not Supported	500E-700E	533EB-733EB	Not Supported	500-600	533-600
	CA63	A	300A-700	800	Not Supported	500E-850E	533EB-1G	Not Supported	500-600	533-600
VIA 694X	CA34	A	300A-700	800	Not Supported	500E-850E	533EB-933EB	Not Supported	500-600	533-600
	CA64-EC/SC/EN/SN	A	300A-700	800	Not Supported	500E-850E	533EB-1G	Not Supported	Not Supported	
		A1	300A-700	800	Not Supported	500E-850E	533EB-1G	Not Supported	500-600	533-600
	TA64-B	A	300A-700	800	Not Supported	500E-850E	533EB-1G	Not Supported	500-600	533-600
	TA64-EN	A	300A-700	800	Not Supported	500E-850E	533EB-933EB	Not Supported	500-600	
	CA64-SU	A	300A-700	800	Not Supported	500E-850E	533EB-933EB	Not Supported	Future VIA Cyrix III Processor	
	CA64-BC/BN	A	300A-700	800	Not Supported	500E-850E	533EB-1G	Not Supported		
	CA64-BC/BN	C	566-700	800-950	Not Supported	500E-850E	533EB-1G	Not Supported		
VIA 694T	CA64-LN	A	300A-766	800	Not Supported	500E-850E	533EB-1G	Not Supported		
	CA64-TC/TN	A	566-700	800-1.1G	Not Supported	500E-850E	533EC-1G	Not Supported	700-750	733
	CA64-TC/TN	BA0	566-700	800-1.1G	≥1.2G	500E-850E	533EC-1G	1.13G-1.26G	700-750	733
VIA Pro266	CD70-SC	A	300A-700	800	Not Supported	500E-850E	533EB-1G	Not Supported	Future VIA Cyrix III Processor	
VIA PLE133	CM33-EC/SC	A	300A-766	800	Not Supported	500E-850E	533EB-1G	Not Supported	Future VIA Cyrix III Processor	
VIA PLE133T	CM33-TC/TL	A	566-700	800-1.1G	≥1.2G	500E-1.1G	533EB-1G	1.13G-1.26G	Future VIA Cyrix III Processor	